

Team #: _____
 Absent: _____

Name: _____

ASCII Character Representation

0	NUL	16	DLE	32		48	0	64	@	80	P	96	`	112	p
1	SOH	17	DC1	33	!	49	1	65	A	81	Q	97	a	113	q
2	STX	18	DC2	34	"	50	2	66	B	82	R	98	b	114	r
3	ETX	19	DC3	35	#	51	3	67	C	83	S	99	c	115	s
4	EOT	20	DC4	36	\$	52	4	68	D	84	T	100	d	116	t
5	ENQ	21	NAK	37	%	53	5	69	E	85	U	101	e	117	u
6	ACK	22	SYN	38	&	54	6	70	F	86	V	102	f	118	v
7	BEL	23	ETB	39	'	55	7	71	G	87	W	103	g	119	w
8	BS	24	CAN	40	(56	8	72	H	88	X	104	h	120	x
9	HT	25	EM	41)	57	9	73	I	89	Y	105	i	121	y
10	LF	26	SUB	42	*	58	:	74	J	90	Z	106	j	122	z
11	VT	27	ESC	43	+	59	;	75	K	91	[107	k	123	{
12	FF	28	FS	44	,	60	<	76	L	92	\	108	l	124	
13	CR	29	GS	45	-	61	=	77	M	93]	109	m	125	}
14	SO	30	RS	46	.	62	>	78	N	94	^	110	n	126	~
15	SI	31	US	47	/	63	?	79	O	95	_	111	o	127	DEL

Abbreviations

NUL	Null	DLE	Data link escape
SOH	Start of heading	DC1	Device control 1
STX	Start of text	DC2	Device control 2
ETX	End of text	DC3	Device control 3
EOT	End of transmission	DC4	Device control 4
ENQ	Enquiry	NAK	Negative acknowledge
ACK	Acknowledge	SYN	Synchronous idle
BEL	Bell (beep)	ETB	End of transmission block
BS	Backspace	CAN	Cancel
HT	Horizontal tab	EM	End of medium
LF	Line feed, new line	SUB	Substitute
VT	Vertical tab	ESC	Escape
FF	Form feed, new page	FS	File separator
CR	Carriage return	GS	Group separator
SO	Shift out	RS	Record separator
SI	Shift in	US	Unit separator
		DEL	Delete/Idle

Team #: _____

Name: _____

Absent:

1) The ASCII code for character 'A' is 65_{10} , 'B' is 66_{10} , ... and 'a' is 97_{10} , 'b' is 98_{10} ,

a) What would be the 7-bit binary value used to represent 'A'?

b) What would be the 7-bit binary value used to represent 'a'?

c) How does an upper-case letter differ from its corresponding lower-case letter?

d) Even parity prepends a 0 or 1 so as to make the total number of 1's be even. What is the 8-bit ASCII value for 'A':

'a':

e) What error cannot be detected by even parity?

2 a) For the 8-bit data 01001011_2 develop the Hamming codeword for one-bit error detection and correction:

12	11	10	9	8	7	6	5	4	3	2	1
D ₇	D ₆	D ₅	D ₄	P ₈	D ₃	D ₂	D ₁	P ₄	D ₀	P ₂	P ₁
0	1	0	0		1	0	1		1		
4+8	1+2+8	2+8	1+8	8	1+2+4	2+4	1+4	4	1+2	2	1

Check bit P₁ looks at bit positions 1, 3, 5, 7, 9, and 11

Check bit P₂ looks at bit positions 2, 3, 6, 7, 10, and 11

Check bit P₄ looks at bit positions 4, 5, 6, 7, and 12

Check bit P₈ looks at bit positions 8, 9, 10, 11, and 12

b) If bit D₅ gets flipped (an error), then how would we be able to detect an error?

c) If bit D₅ gets flipped (an error), then how would we be able to know which bit to correct?

d) For the 8-bit data 11001001_2 develop the Hamming codeword for one-bit error detection and correction:

12	11	10	9	8	7	6	5	4	3	2	1
D ₇	D ₆	D ₅	D ₄	P ₈	D ₃	D ₂	D ₁	P ₄	D ₀	P ₂	P ₁
0	1	0	0		1	0	1		1		
4+8	1+2+8	2+8	1+8	8	1+2+4	2+4	1+4	4	1+2	2	1